



A new meter collar device that makes connecting a portable generator safe and easy

Connecting A Portable Generator is Now Safe and Easy with GenerLink™



SAFE

GenerLink™ eliminates the use of extension cords and other connections that can be hazardous to customers and utility personnel.

GenerLink™ detects when a generator is operating and automatically disconnects from the utility grid, eliminating dangerous backfeed.

EASY

GenerLink™ is equipped with GenerLok™, a unique interlocking power cord system that provides a quick and easy connection of a portable generator.

GenerLink™ is installed in 20 minutes or less by utility personnel and does not require the customer's presence.

GenerLink™ is easily installed behind a customer's electric meter and requires no rewiring of the customer's electrical system.

With GenerLink™, customers have the flexibility to run virtually any appliance, up to the capacity of their generator by simply energizing appliances from their breaker panel.

GENERLINK™ with GENERLOK™ SPECIFICATIONS AND TECHNICAL INFORMATION MODEL MA23/24 - N/S

Physical:	Diameter:	6 ½ in.
	Depth:	5 ¼ in.
	Weight w/o surge:	5 ½ lbs
	Weight with surge:	5 ¾ lbs
	Socket Style:	Ring or Ring-less, 200 Amp, 4 jaw
Electrical:	Source Compatibility	200 Ampere Service or less
	Withstand Current:	14,000 Amperes rms symmetrical at .5 pf, 240 Volts, 60 Hz 6000 Amperes for 6 cycles at .7 - .8 pf, 240Volts, 60 Hz
	Generator Input:	10kW Continuous†, 120/240 Volt (MA-24)
	Connection:	Proprietary GenerLok™ QuickConnect Power Cord‡
Operational:	Transfer Type:	Break-Before-Make
	Transfer Delay:	2-3 Seconds
	Life Cycle:	300,000 Operations
	Temperature Range:	-30°C to 60°C External Ambient
Features:	Generator Input Protection:	Generator Input Voltage ≥ 200 Volts Supplemental Overcurrent ≤ 40 A
	Utility Input Protection:	Utility Input Voltage ≥ 180 Volts Over-Temperature Trip ≥ 105°C
	Load Protection:	Integrated Whole-House, Surge Protection Model MA23/24 - S Only Type 1 - 75kA per phase
	Status Indication:	Long-life LED indicators show utility power availability and/or fault presence
	Listings:	UL 1008M - Meter socket transfer switch

† 3 hours at 25° C ambient

‡ Sold Separately

* when protected by max 200 A circuit breaker in series with max 100 A branch circuit breaker